



Features & Benefits

- Selectable mode of operation either 0-10V or 0-20mA
- 12 bit resolution
- Simple, quick installation
- Easy configuration via USB/downlink
- Battery life 3+ years*
- Signal and battery indicator

Technical Overview

Voltage (0-10V) or Current (0-20mA) is converted to LoRaWAN so the device data can be displayed and analysed.

Technical Specification

Radio output type	LoRaWAN
Battery Life	3+ Years
Housing Dimensions	129 x 67 x 41mm
Batteries	SAFT LS14500 or EVE ER14505 AA size 3.6 Volt Lithium Thionyl Chloride (Li-SOCl ₂) batteries (non-rechargeable) or direct equivalent
Security	AES 128 encryption
Housing colour	Black
IP Rating	IP40 / NEMA 1. Optional gasket: IP67 / NEMA 4
Compliance	UKCA, CE, FCC compliant
Country of origin	UK

Related Product Codes

RF-LW-VC-IN	LoRaWAN Voltage and Current converter
-------------	---------------------------------------