

Product datasheet

Specifications



"Standard for PanelSeT S3D encl. RAL7035, L140xW80"

Local distributor code:

392870171

NSYTLA

EAN Code: 3606480168529

Main

Range	PanelSeT
Product or component type	Cable gland plate
Accessory / separate part category	Cable management accessory
Application	Multi-purpose
Range compatibility	PanelSeT S3D
Mounting location	Enclosure bottom
Cable gland type	Standard
Device composition	fixing elements 1 plate 1 separate gasket
Quantity per set	Set of 1
Material	Plate: steel Seal: polyethylene (PE) foam

Complementary

Colour	Plate: grey (RAL 7035)
Surface finish	Epoxy-polyester powder
Number of cut-out	3 markings 25 mm
Height	140 mm
Width	140 mm Real: 200 mm
Depth	80 mm Real : 400 mm
Product weight	190 kg
thickness	1.5...2.0 mm

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	1.000 cm
Package 1 Width	10.000 cm
Package 1 Length	17.000 cm
Package 1 Weight	194.000 g

Logistical informations

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Country of origin	FR
-------------------	----

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)



Environmental footprint

Environmental Disclosure

[Product Environmental Profile](#)

Use Better



Materials and Substances

Packaging made with recycled cardboard	No
Packaging without single use plastic	No
SCIP Number	E893f0a0-d2cc-4011-9425-3873dde70142
EU RoHS Directive	Compliant
REACH Regulation	Free of Substances of Very High Concern above the threshold

Use Longer



Lifetime extension

Repair	No
--------	----

Use Again



Repack and remanufacture

End of life manual availability	No need of specific recycling operations
Take-back	No